

## Fluke 355 and 353 True-rms 2000 A Clamp Meters

### Versatile and rugged tools for applications with high currents



Confidently take reliable readings with the True-rms, Fluke 355 and 353 digital clamp meters; the tools of choice for high current clamp-on amp meter measurement up to 2000 A. The extra-wide jaw easily clamps around large conductors, typically found in high-current applications. The extra rugged design and CAT IV 600 V, CAT III 1000 V ratings add an extra element of user protection when taking high-powered measurements.

Accurate peak measurements can be taken using the in-rush current mode, ideal for motors and inductive loads. The 355 also measures voltage and resistance, making this an ideal clamp meter for utilities, electrical contractors and industrial service technicians.



- Reliably handle a wide range of high-current applications with 2000 A ac + dc true-rms, 1400 A ac, and 2000 A dc
- The large 58 mm (2.3 in) jaw capacity is suitable for large or multiple conductors
- CAT IV 600 V, CAT III 1000 V rating for added user protection
- In-rush current measurement captures 'power-on' surge current with accuracy and repeatability
- High voltage measurement of 1000 V ac + dc true-rms, 600 V ac, and 1000 V dc allows the user to perform multiple tests with only one tool (355 only)
- Resistance to 400K ohms coupled with a continuity beeper provide the convenience of a multimeter in a clamp meter. (355 only)
- Accurately measure frequency up to 1 kHz for optimum troubleshooting
- Quickly analyze readings using the MIN, MAX, and AVG functions
- A large backlit display allows for easy visibility in low-lit areas
- Use the display hold feature to capture readings even when the display cannot be viewed
- Use the low-pass filter to smooth out noisy loads and stabilize readings

# Fluke 355 and 353 True-rms 2000 A Clamp Meters



Electrical specifications		
Current measurement dc and ac 10 Hz to 100 Hz	Range : 40 A	Resolution: 10 mA Accuracy, A: 1.5 % rdg + 15 digits Trigger Level for Inrush: 0.50 A Trigger Level for Hz Filter OFF: 2.50 A Trigger Level for Hz Filter ON: 0.50 A
	Range : 400 A	Resolution: 100 mA Accuracy, A: 1.5 % rdg + 5 digits Trigger Level for Inrush: 5.0 A Trigger Level for Hz Filter OFF: 2.5 A Trigger Level for Hz Filter ON: 2.5 A
	Range : 2000 A; 1400 ac rms	Resolution: 1 A Accuracy, A: 1.5 % rdg + 5 digits Trigger Level for Inrush: 5 A Trigger Level for Hz Filter OFF: 8 A Trigger Level for Hz Filter ON: 8 A
Crest Factor (50/60 Hz)	Range : 40 A	Crest Factor* : 2 @ 33 A, 2.4 @ 27 A
	Range : 400 A	Crest Factor* : 2 @ 330 A, 2.4 @ 270 A
	Range : 2000 A; 1400 ac rms	Crest Factor* : 2 @ 1000 A, 2.4 @ 833 A
Current measurement ac 100.1 Hz to 1 kHz	Range : 40 A	Resolution: 10 mA Accuracy > 10 A : 3.5 % rdg + 15 digits Trigger Level for Inrush: 0.50 A Trigger Level for Hz Filter OFF : 2.50 A Trigger Level for Hz Filter ON : 0.50 A
	Range : 400 A	Resolution: 100 mA Accuracy > 10 A : 3.5 % rdg + 5 digits Trigger Level for Inrush: 5.0 A Trigger Level for Hz Filter OFF : 2.5 A Trigger Level for Hz Filter ON : 2.5 A
	Range : 2000 A; 1400 ac rms	Resolution: 1 A Accuracy > 10 A : 3.5 % rdg + 5 digits Trigger Level for Inrush: 5 A Trigger Level for Hz Filter OFF : 8 A Trigger Level for Hz Filter ON : 8 A

<b>Voltage measurement (355 only) dc and ac 10 Hz to 100 Hz (600 V and 1000 V ranges have 10 % over range to 660 V and 1100 V respectively.)</b>	<b>Range : 4 V</b>	Resolution: 1 mV Accuracy: 1 % rdg + 10 digits Trigger Level for Hz Filter OFF: 0.050 V Trigger Level for Hz Filter ON: 0.050 V
	<b>Range : 40 V</b>	Resolution: 10 mV Accuracy: 1 % rdg + 5 digits Trigger Level for Hz Filter OFF: 0.25 V Trigger Level for Hz Filter ON: 0.25 V
	<b>Range : 400 V</b>	Resolution: 100 mV Accuracy: 1 % rdg + 5 digits Trigger Level for Hz Filter OFF: 6 V Trigger Level for Hz Filter ON: 6 V
	<b>Range : 600 V ac rms</b>	Resolution: 1 V Accuracy: 1 % rdg + 5 digits Trigger Level for Hz Filter OFF: 6 V Trigger Level for Hz Filter ON: 6 V
	<b>Range : 1000 V dc</b>	Resolution: 1 V Accuracy: 1 % rdg + 5 digits
<b>Voltage measurement (355 only) ac 100.1 Hz to 1 kHz (600 V and 1000 V ranges have 10 % over range to 660 V and 1100 V respectively.)</b>	<b>Range: 4 V</b>	Resolution: 1 mV Accuracy: 3 % rdg + 10 digits Trigger Level for Hz Filter OFF: 0.050 V Trigger Level for Hz Filter ON: 0.050 V
	<b>Range: 40 V</b>	Resolution: 10 mV Accuracy: 3 % rdg + 5 digits Trigger Level for Hz Filter OFF: 0.25 V Trigger Level for Hz Filter ON: 0.25 V
	<b>Range: 400 V</b>	Resolution: 100 mV Accuracy: 3 % rdg + 5 digits Trigger Level for Hz Filter OFF: 6 V Trigger Level for Hz Filter ON: 6 V
	<b>Range: 600 V ac rms</b>	Resolution: 1 V Accuracy: 3 % rdg + 5 digits Trigger Level for Hz Filter OFF: 6 V Trigger Level for Hz Filter ON: 6 V
<b>Ohms measurement (355 only)</b>	<b>Range: 400 <math>\Omega</math></b>	Resolution: 0.1 $\Omega$ Accuracy: 1.5 % + 5 digits
	<b>Range: 4 k<math>\Omega</math></b>	Resolution: 1 $\Omega$ Accuracy: 1.5 % + 5 digits
	<b>Range: 40 k<math>\Omega</math></b>	Resolution: 10 $\Omega$ Accuracy: 1.5 % + 5 digits
	<b>Range: 400 k<math>\Omega</math></b>	Resolution: 100 $\Omega$ Accuracy: 1.5 % + 5 digits
<b>Continuity beeper (355 only)</b>	On at $\leq 30 \Omega$ Off at $\geq 100 \Omega$	
<b>Frequency measurement</b>	<b>Measurement range</b>	5.0 Hz to 1 kHz
	<b>Resolution</b>	0.1 Hz (15 Hz to 399.9 Hz); 1 Hz (400 Hz to 1 kHz)
	<b>Accuracy – 5.0 Hz to 100 Hz</b>	0.2 % + 2 counts
	<b>Accuracy – 100.1 Hz to 1 kHz</b>	0.5 % + 5 counts
	<b>Trigger level</b>	Refer to current and voltage tables

\*Add 2 % to error spec for CF > 2

<b>General specifications</b>	
<b>Batteries</b>	Six 1.5 V AA NEDA 15 A or IEC LR6
<b>Battery life (with typical usage, backlight off)</b>	100 hours
<b>Test leads</b>	Rated to 1000 V
<b>Weight</b>	.814 kg (1.8 lb)
<b>Jaw size</b>	58 mm (2.28 in)
<b>Dimensions (LxWxD)</b>	300 mm x 98 mm x 52 mm (12 in x 3.75 in x 2 in)
<b>Safety rating</b>	IEC 61010-2-032, 600 V CAT IV, 1000 V CAT III

<b>Environmental specifications</b>	
<b>Operating temperature</b>	32 °F to + 122 °F (0 °C to +50 °C)
<b>Storage temperature</b>	-4 °F to 140 °F (-20 °C to +60 °C)
<b>Operating humidity</b>	0 to 95 % (non-condensing)
<b>Operating altitude</b>	2000 m
<b>Storage altitude</b>	10,000 m
<b>IP rating</b>	42 (indoor use only)
<b>Drop test requirements</b>	1 m
<b>EMI, RFI, EMC</b>	FCC part 15, IEC/EN 61326-1:1997 class B, IEC/EN 61326:1997 3V/m, performance criteria B, EN61325
<b>Temperature coefficients</b>	<b>Current:</b> 0.1 % of reading per °C outside 22 °C to 24 °C <b>Voltage:</b> 0.1 % of reading per °C outside 22 °C to 24 °C

## Fluke 355 and 353 True-rms 2000 A Clamp Meters

Model Name	Product Description	
Fluke 353	AC/DC TRMS CLAMP METER,2000A,AMPS ONLY  Includes: <ul style="list-style-type: none"> <li>● 353 clamp meter</li> <li>● C43 Soft carrying case</li> <li>● 6 AA batteries</li> <li>● User manual</li> <li>● 3 year warranty</li> </ul>	
Fluke 355	AC/DC TRMS CLAMP METER,2000A  Includes: <ul style="list-style-type: none"> <li>● 355 clamp meter</li> <li>● C43 Soft carrying case</li> <li>● 6 AA batteries</li> <li>● TL224 1.5 m silicone rubber test leads</li> <li>● TP2 Test Probes</li> <li>● AC285 Alligator Clips</li> <li>● User manual</li> <li>● 3 year warranty</li> </ul>	